

Argus PT (5/2.4GHz)

5MP battery/solar powered IP camera with pan & tilt, dual-band Wi-Fi, high-quality color night vision, AI detection and active deterrence.

- 2K 4MP Super HD
- Person/Vehicle Detection
- Battery/Solar Powered

Specifications

Video & Audio	
Image Sensor	1/2.7"CMOS sensor
Resolution	2880 x 1616 (5 megapixels) @15fps
Video Compression	H.265
Field of View	Horizontal: 90° Vertical: 47° Diagonal: 110°
Infrared Night Vision	Up to 10 meters (33ft); LED: 2pcs/1.2w/850nm (Auto-switching with IR-cut filter)
Color Night Vision	With spotlights: 2pcs/2.4w/6500k
Frame Rate	Main stream: 10fps - 15fps (default: 15fps) Sub stream: 10fps - 15fps (default: 15fps)
Code Rate	Main stream: 1024Kbps - 4096Kbps (default: 3072Kbps) Sub stream: 64Kbps - 672Kbps (default: 672Kbps)
Audio	Two-way audio

Power	
Battery	21.6Wh rechargeable battery (Battery life varies based on settings, usage & temperature.)
Solar	Reolink Solar Panel (3W)
Interface	
Power Port	USB Type-C port
SD Card Slot	Supports Max. 128GB microSD card
Reset Button	YES
Audio In/Out	Built-in microphone and speaker
Pan & Tilt	
PT Angle(Max.)	Pan: 355°, Tilt: 140°
Preset Points	64
Wi-Fi	
Wireless Standard	IEEE 802.11 a/b/g/n
Operating Frequency	2.4GHz/5GHz
Wireless Security	WPA/WPA2
Software	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P
User Access	Max. 12 simultaneous streams (2 main & 10 sub streams)
Other Features	
Smart Alarm	PIR detection; person detection; vehicle detection; pet detection
PIR Detecting Distance	Adjustable up to 10m (33ft)
PIR Detecting Angle	120° horizontal
Recording Modes	Triggered recording

Time Lapse	YES
Smart Home Compatibility	Google Assistant; Alexa
Cloud Storage	Supports Reolink Cloud (available in selected countries)
Working Environment	
Operating Temperature	-10°C~+55°C (14°F~131°F)
Operating Humidity	20% ~ 85%
Weatherproof	IP64
Mechanical	
Dimensions	Φ98 x 122mm
Weight Battery Included	477g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ .

Gallery & Specs



1. Speaker
2. Lens
3. Daylight Sensor
4. 6 IR LEDs
5. Status LED
6. Built-In PIR Sensor
7. Built-In Mic



1. Antenna
2. Micro USB Port
3. Power Switch
4. Micro SD Card Slot
5. Reset Hole

www.reolink.com